

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets

33



(11)

98P2729
EP 0 709 825 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
01.05.1996 Bulletin 1996/18

(51) Int. Cl.⁶: G09G 5/36, G09G 1/16

(21) Application number: 95113128.3

(22) Date of filing: 21.08.1995

(84) Designated Contracting States:
CH DE FR GB LI NL

(30) Priority: 07.09.1994 US 301622

(71) Applicant: HARRIS CORPORATION
Melbourne, Florida 32919 (US)

(72) Inventors:

- Malinowski, Christopher W.
Melbourne, Florida 32951 (US)
- Zepp, Stanley R.
Melbourne, Florida 32901 (US)

(74) Representative: Fleuchaus, Leo, Dipl.-Ing. et al
Melchiorstrasse 42
D-81479 München (DE)

(54) Video scaling method and device

(57) A linear interpolator and decimating FIR filter with constant coefficients in various configurations to scale a still or moving color video image horizontally or vertically. For downscaling, the input pixel stream is initially upsampled with an interpolator by an upscaling factor of between one and two chosen so that the result can be

subsequently downsampled with a decimation-by-power-of-two finite impulse response (FIR) filter. Upscaling is accomplished by means of linear interpolation. Vertical and horizontal scaling may be performed with different, independent scaling factors.




FIG. 5

EP 0 709 825 A2

Description

The present invention relates to video image resizing architectures, and particular to a device and method for scaling a still or moving video image comprised of a first plurality of digital picture elements (known as pixels) in order to replicate the image with a second plurality of pixels.

A digital video image comprises an array of pixels, with the number of pixels in each horizontal row and vertical column being determined by the system in which the image is formed. When the image is to be displayed in a system that uses the same number of pixels in each row as the input image and the same number of pixels in each column as the input image, the image may be displayed directly. However, when the image is to be displayed in a system that uses a different number of pixels in each row and/or a different number of columns as the input image, the image must be scaled so that the same image can be displayed in the new array of pixels. For example, an image comprising a 500 by 750 array of pixels must be scaled up before it can be displayed in a system that uses an array of 750 by 900 pixels. Conversely, the same image may need to be scaled down before it can be displayed in a system using an array of only 250 by 350 pixels. As is apparent, the horizontal and vertical scaling factors may not be the same. Similar scaling steps may be required when a portion of an image on a display is to be enlarged to fill the entire display or when an image on a display is to be reduced and provided as a small inset in the display.

Digitized color video images are typically comprised of pixels that include data bits for luminance (Y) and for chrominance (U, V), and may have, for example, eight data bits for each of the Y, U and V components (other color component systems, such as Red, Green, Blue (RGB), being equivalent.) When a color image is scaled for display in another system, each of the color components must be scaled.

Video images are desirably scaled in real-time (i.e. at the rate they are delivered to the video processing system) when upscaling (increasing the number of pixels per image) or downscaling (decreasing the number of pixels per image.)

When an image is to be scaled, an input stream of pixels may be mapped to an output stream by interpolation. For example, when an image is to be scaled using linear interpolation, the input stream of pixels may be mapped into increments dx , where $dx=1/K$ and K is a scaling factor. As illustrated in Figure 1, with an upscaling $K = 3/2$ ($dx = 2/3$), an input stream of six pixels may be mapped into nine increments that will become nine output pixels. The value of each of the nine output pixels may be determined by interpolating between corresponding pixels in the input stream.

An object of the present invention to provide a device and method for scaling a video image, and to provide a device and method for real-time upscaling or downscaling a video image, and in which interpolation and subsequent decimation are performed without skipping pixels, rows or lines to provide a high quality scaled image, and also for real-time upscaling or downscaling a video image in which buffer size requirements are reduced and the number of buffers is minimized without limiting downscaling capability.

A further object is to provide a device and method for scaling a video image in which upscaling is accomplished with a single pixel or line buffer component and linear interpolator, and downscaling is accomplished with an upscaling linear interpolator and decimating FIR filter where the number of filter taps (i.e. bandwidth) is related to the decimating factor.

The present invention includes a device for scaling an input of a first plurality of pixels arrayed in horizontal rows and vertical columns that form an image in order to provide an output of a second plurality of pixels that forms the image, the device comprising as a set an upscaling interpolator comprising (a) a buffer for storing the input pixels, and (b) a linear interpolator that sequentially receives each of the stored input pixels from said buffer and the pixel subsequent thereto for providing interpolated output pixels therefrom responsive to a predetermined upscaling factor, a decimating finite impulse response (FIR) filter for reducing the number of output pixels from said upscaling interpolator responsive to a predetermined downscaling factor, said second plurality being equal to said first plurality times said upscaling and downscaling factors, and in which repetitive operation of said set of said upscaling interpolator and said decimating FIR filter will provide an output of the second plurality of pixels that forms the image.

The invention also includes a method of scaling an input of a first plurality of pixels that form an image to provide an output of a second plurality of pixels that forms the image, the method comprising the steps of:

- (a) upscaling the input pixels in an interpolator responsive to an upscaling factor; and
- (b) decimating the upscaled pixels in decimation-by-power-of-two-FIR filter, the upscaling factor being selected so that the subsequent decimation by power of two provides the second plurality of pixels.

The invention will now be described by way of example, with reference to the accompanying drawings in which

Figure 1 is an illustration of mapping an output image size onto an input stream of pixels that may be used in linear interpolation.

Figure 2 is a block diagram of an embodiment of an interpolator.

Figure 3 is an illustration of operation of the linear interpolator of Figure 2.

Figure 4 is a block diagram of an embodiment of a decimating filter.

Figure 5 is a block diagram of an embodiment of a scaling device.

Figure 6 is a block diagram of an embodiment of a color video scaling device.

A device and method for scaling a moving or still video image may include an interpolator for upscaling and a decimating filter for downscaling. The upscaling interpolator may use an upscaling factor chosen so that the desired scaling of the image may be achieved by subsequent decimation in a decimation-by-power-of-two finite impulse response (FIR) filter. These two components may be used in several image scaling arrangements, including color image scaling, that will be discussed in detail following separate descriptions of the interpolator and filter. For example, the two components may be used as a set, and two sets may be paired to provide vertical and horizontal scaling in which the vertical and horizontal scaling factors need not be the same.

Figure 2 illustrates an upscaling interpolator 20 with a buffer 22 for storing pixels from an input stream of pixels 24, and a linear interpolator 26 that sequentially receives each of the stored input pixels from the buffer 22 and the pixel subsequent thereto from the input stream 24 for providing an output of interpolated pixels 28 responsive to a predetermined upscaling factor K. The upscaling interpolator 20 provides an output stream with more pixels per image than the input stream, such as illustrated in Figure 1. That is, an input stream of six pixels will become an output stream of nine pixels (with $K = 3/2$). The same structure may be used for horizontal scaling, in which event the buffer is a pixel buffer, or for vertical scaling in which event the buffer is a line buffer with its length equal to the number of pixels per line.

Each input pixel is first stored in the buffer 22 and then provided to the linear interpolator 25 so that it may be evaluated with the next pixel. In the linear interpolator 26 the size of the pixels in the output stream is mapped onto the input stream of pixels by stepping across the input stream in increments dx (such as illustrated in Figure 1). Since this is an upscaling interpolator, the increment dx is less than one (i.e., $K > 1$). The stepping operation may be accomplished in an accumulator that adds the number of increments dx across the image (Σdx). The fractional part of Σdx , designated Δx and shown in Figure 1, is the fractional distance between two input pixels that will be used to find the interpolated value for an output pixel therebetween. Mathematically,

$$\Delta x = \Sigma dx \text{ Modulo } 1 \quad (1)$$

The next step is to use Δx and the values of the neighboring pixels to calculate the interpolated value for the output pixel. This calculation may be understood with reference to Figure 3 that is an expanded view of a portion of a stream 30 of input pixels Y1, Y2, Y3, etc. in which input pixel values are indicated by vertical bars 32. The interpolated values of the output pixels may be determined using:

$$Z1 = Y1 + (Y2 - Y1)\Delta x \quad (2)$$

where, Z1 is the interpolated value of the output pixel between input pixels Y1 and Y2, and is illustrated in Figure 3 by the vertical bar 34.

With reference again to Figure 2, this calculation may be performed in the linear interpolator 26 that receives the value of Y1 from buffer 22 and the value of the subsequent pixel Y2 from the input stream 24. The value of Z1 is sent in the output stream 28.

As may be seen in Figure 3, there may be situations where more than one interpolation calculation is required for a pair of input pixels. For example, two output pixels Z2 and Z3 fall between input pixels Y2 and Y3. The value of Z2 may be calculated as discussed above, and the value of Z3 may be calculated by substituting the value $(\Delta x + dx)$ for the value Δx . In general, for a given set of input pixels, interpolations are generated so long as the accumulation of dx does not increment beyond the next integer pixel value. For an upscaling factor of K, the average number of interpolations per input pixel is K, and the maximum number of interpolations is the integer part of $K + 1$, while the minimum number of interpolations is the integer part of K.

The precision required for the fractional part of dx (that is, the number of bits needed to represent dx) is governed by the interpixel precision needed and the number of times dx is stepped across the image. For example, if it is known that the number of pixels will be no greater than 768 pixels per line, then the worst case output pixel phase jitter is two nanoseconds at 13.5 Mhz (corresponding to $1/37.037$ of one inter-pixel time span), and six bits of interpixel precision will be required. Further, as dx will be summed over 768 pixels, ten bits of additional precision will be needed for the sum. Therefore, dx must have a fractional precision of sixteen bits. In this example, the precision requirement for Δx is six bits and Δx may be calculated by rounding the output of the dx accumulator to six bits.

Figure 4 shows a decimating filter 40 may receive the output stream 28 of interpolated pixels from the interpolator 20. Filter 40 includes a decimating finite impulse response (FIR) filter 42 and a buffer 44. The output 46 from the decimating filter 40 is a stream of correctly scaled pixels that form an array of pixels that represents the input image. When the filter 40 is being used a vertical filter the buffer 44 may include two line buffers, and when the filter 40 is being used as a horizontal filter the buffer 44 may include a minimum number of pixel buffers, desirably two.

The FIR filter 42 decimates the number of input pixels by a decimating factor equal to a predetermined power of two. The filter may operate by accumulating filter calculations in buffer 44 for a number of the filter taps and then calculating the remainder of the filter and dumping the buffer at the decimated rate. For a decimating factor of D , a FIR filter with $D + 1$ taps may be used. For example, a three tap filter will decimate by 2, a five tap filter will decimate by 4, a nine tap filter will decimate by 8, etc. Each of these $D + 1$ tap filters has only one set of constant coefficients which are predetermined and set to achieve the desired bandwidth for that filter. For example, a five tap filter that decimates by 4 would have one set of coefficients designed to limit the bandwidth to $1/8$ the input sampling frequency. The filters are desirably symmetric. That is, the five coefficients for a five tap filter would be C_0, C_1, C_2, C_1, C_0 .

The operation of the decimating filter 40 may be more clearly seen by reference to three examples, a two-to-one decimation, a four-to-one decimation, and an eight-to-one decimation. In two-to-one decimation, the FIR filter 42 has three taps which are generated and output for every other interpolated input. Note that the interpolated input may include two output pixels between some pairs of input pixels (for example output pixels Z2 and Z3 in Figure 3) and these two output pixels of the interpolator will be referred to as Z_a and Z_b . The sequence of operation of the filter 42 is shown below in the various states of its operation. The filter is symmetric and includes coefficients C_0, C_1 , and C_0 .

State 0	Start-up operation; no interpolation. (Input from interpolator 26)
State 1	$Z_a \cdot C_0 + Z_b \cdot C_1 = \text{buffer input}$
State 2	$Z_a \cdot C_0 + \text{buffer output} = \text{output 46}$ $Z_a \cdot C_0 + Z_b \cdot C_1 = \text{buffer input}$
State 3	$Z_a \cdot C_0 + \text{buffer output} = \text{output 46}$ $Z_a \cdot C_0 = \text{buffer input}$
State 4	$Z_a \cdot C_1 + Z_b \cdot C_0 = \text{output 46}$ $Z_b \cdot C_0 = \text{buffer input}$

Note that two multiplications are required for the filter calculations and two for the interpolation for a total of four multiplications per input pixel. The coefficients may be set to provide a bandwidth of $1/2$ the input sampling rate.

In four-to-one decimation, a five tap filter is implemented before output pixels are dumped every fourth clock. Coefficients may be set to provide a bandwidth of $1/8$ the input sampling rate. In this example the interpolation pattern repeats every three inputs and the output pattern repeats every four interpolations.

State 0	Start-up operation; no interpolation (Input from interpolator 26)
State 1	$Z_a \cdot C_0 + Z_b \cdot C_1 = \text{buffer input}$
State 2	$Z_a \cdot C_2 + Z_b \cdot C_1 + \text{buffer output} = \text{buffer input}$
State 3	$Z_a \cdot C_0 + \text{buffer output} = \text{output 46}$ $Z_a \cdot C_0 = \text{buffer input}$
State 4	$Z_a \cdot C_1 + Z_b \cdot C_2 + \text{buffer output} = \text{buffer input}$
State 5	$Z_a \cdot C_1 + Z_b \cdot C_0 + \text{buffer output} = \text{output 46}$ $Z_b \cdot C_0 = \text{buffer input}$

In eight-to-one decimation, a nine tap filter is implemented before output pixels are dumped every eight output samples. Coefficients may be set to provide a bandwidth of $1/16$ the input sampling rate. As in the above, a maximum

of four multiplications are required per input pixel.

State 0	Start-up operation; no interpolation (Input from interpolator 26)
State1	$Za \cdot C0 + Zb \cdot C1 = \text{buffer input}$
State2	$Za \cdot C2 + Zb \cdot C3 + \text{buffer output} = \text{buffer input}$
State3	$Za \cdot C4 + \text{buffer output} = \text{buffer input}$
State4	$Za \cdot C3 + Zb \cdot C2 + \text{buffer output} = \text{buffer input}$
State5	$Za \cdot C1 + Zb \cdot C0 + \text{buffer output} = \text{output 46}$
	$Zb \cdot C0 = \text{buffer input}$

The interpolator and filter may be used in various configurations depending on the scaling to be performed. The components may be used to scale horizontally (changing the number of pixels per row) and to scale vertically (changing the number of pixels per column). These operations may be performed independently without regard to which scaling is performed first and with different horizontal and vertical scaling factors, K_h and K_v . It may be desirable to perform the vertical upscaling first so that the buffers used for vertical upscaling do not have to store the upscaled number of pixels in the horizontal rows and may be at minimum length.

For downscaling, the input pixel stream is initially upsampled by an upscaling factor of between one and two chosen so that the result can be subsequently downsampled by a power of two to provide the desired final scaling. For example, if a final scaling of 5/8 is desired, the input pixels may be initially upsampled by a factor of 5/4 in the interpolator 20 and thereafter decimated by a factor of 2 (downsampled by 1/2) in the decimating filter 40. Upscaling is a special case in which there is no decimation and in which the upscaling factor is not limited. In this manner, any final scaling factor may be achieved with simple linear interpolator and power-of-two FIR filter with constant coefficients.

Figure 5 illustrates a scaling device with interpolators 20 and filters 40. An input stream of pixels may be scaled vertically using a first set 48 of interpolator 20 and filter 40, and thereafter scaled horizontally using a second set 50 of interpolator 20 and filter 40 that may be same as the first set 48. The only difference between the vertical and horizontal scaling is that the vertical scaling uses row delays and stores rows of pixels, while the horizontal scaling uses pixel delays and stores a pixel at a time. The sequence of the sets 48 and 50 for horizontal and vertical scaling may be reversed.

The order of the FIR filters (the number of taps) can be changed by changing the number of line or pixel buffers and multipliers. For example, if three, rather than two, line or pixel buffers drive the filter, an N:1 filter would have $N + 3$ taps for scaling factors of from $(1/2 \text{ through } 1)/N$, where N is a power of 2. Two additional multiplications would be required per input pixel.

Color video images may be scaled using the interpolator and filter discussed above. With reference to Figure 6, color video input may be separated into Y and UV components and provided to staged interpolators 52 and filters 54, with the order of vertical and horizontal scaling being dependent on application. The interpolators 52 and filters 54 may each include two sections, each section comprising the interpolator 20 and filter 40 discussed above. The Y and UV components may share a common scaling factor at each stage (the vertical and horizontal scaling factors may be independent.) Alternatively, three separate and parallel scaling operations (one each for the Y, U, and V bits in the pixels) may be used.

The luminance (Y) information in each pixel is desirably scaled as indicated above using all input pixels. Preferably, the U and V information is subsampled in alternating pixels to reduce scaling hardware. By sampling the U and V in a two-to-one ratio, the scaling hardware may be shared so that two parallel scaling operations (e.g., the device illustrated in Figure 6) may be used (one for Y and one alternating between U and V) instead of three.

The U and V components may be sampled in various formats. For example, a 4:2:2 format horizontally subsamples U and V two-to-one relative to Y, but does not subsample vertically. A 4:2:0 format subsamples vertically as well. For

example, the 4:2:2 sampling format (spatial arrangement of two rows of sampled pixels is shown, the pattern repeats) is:

```

Row 1      Y Y Y Y Y Y Y      (luminance)
           0 0  0  0      (chrominance, U or V)

Row 2      Y Y Y Y Y Y Y
           0 0  0  0

```

That is, the data are clocked in as

YUV_yYUV_yYUV_yYUV

and Y, U, and V information is subsampled from every other pixel (shown in capital letters), and the U and V information from the other pixels (shown with a small y) is not subsampled.

The 4:2:0 sampling format (spatial arrangement of four rows of pixels is shown, the pattern repeats) is:

```

Row 1      Y Y Y Y Y Y
           0  00

Row 2      Y Y Y Y Y Y
Row 3      Y Y Y Y Y Y
           0 0    0

Row 4      Y Y Y Y Y Y

```

That is, in the 4:2:0 format U and V information is subsampled 2:1 vertically and horizontally, and there is a one-half pixel offset of U and V information relative to Y information in both directions.

In the 4:2:2 format, an input stream of pixels may be clocked at a fixed clock rate generated by the video source. The input format may be binary words, for example eight bits long, on each clock, with one word being the Y scaler input and the other alternating between U and V. The Y input may be an unsigned eight bit binary number while the U and V may be unsigned or signed two's complement eight bit binary number. The $\Delta_x/4$ used in the U and V calculations, denoted Δ_{uv} , may be the same for both U and V because the spatial relationship between Y and U or V is fixed. This means that Δ_{uv} may be the same as Δ_y or determined by dividing by two, where Δ_y is the Δx for Y.

The process of positioning the U and V outputs relative to the Y outputs may be accomplished in the scaler hardware by a combination of adding a phase offset to the U, V interpolation position relative to the Y position, and (or alternatively) adjusting the phasing the U, V decimating filter relative to the Y filter at the beginning of the row or array. This adjustment may include providing an unfiltered interpolation of the first U, V row or pixel followed by starting the U, V filter at the time that results in subsequent U, V filter outputs being properly positioned.

For example, and with reference to Table 1 below that depicts alternative spatial arrangements of the pixels (phase adjustment being performed in one dimension at a time using the interpolator and/or filter), consider horizontal rescaling a 4:2:2 input to a 4:2:2 output with four-to-one decimation. As may be seen in the middle section of Table 1, proper output positioning occurs when $\Delta_{duv} = 1/2 \Delta_{dy}$, and the second U, V interpolation is output directly (a point output with no filtering) followed by starting the U, V filter on the seventh Y interpolation ($n = 6$, where n is the number of consecutive input pixel Y interpolations as counted (beginning from 0) from the beginning of the pixel row.) This corresponds to the fourth U, V interpolation. Table 1 also includes examples of two-to-one decimation for 4:2:2 and 4:2:0 output formats, and illustrates how this method of scaling can facilitate video format conversions. Similar examples of vertical rescaling are shown in Table 2.

Table 3 summarizes scaling options available in a device incorporating the present invention that is used as a NTSC/PAL decoder/scaler (4:2:2 input) in which downscaling includes 2:1, 4:1 and 8:1 decimations and upscaling is 1:1.2 (vertical only, horizontal upscaling is not needed in this particular application.)


A linear interpolator and decimating FIR filter with constant coefficients in various configurations to scale a still or moving color video image horizontally or vertically. For downscaling, the input pixel stream is initially upsampled with an

interpolator by an upscaling factor of between one and two chosen so that the result can be subsequently downsampled with a decimation-by-power-of-two finite impulse response (FIR) filter. Upscaling is accomplished by means of linear interpolation. Vertical and horizontal scaling may be performed with different, independent scaling factors.


TABLE 1

U/V VS Y PIXEL SITING, HORIZONTAL


4:2:2 > 4:2:2 HORIZONTAL DOWNSCALE, 2:1



4:2:2 > 4:2:2 HORIZONTAL DOWNSCALE, 4:1



4:2:2 > 4:2:0 HORIZONTAL DOWNSCALE, 2:1



LEGEND:

Y Y PIXEL INPUT/OUTPUT

O U OR V PIXEL INPUT/OUTPUT

I MAPPED INTERPOLATION POINT (OUTPUT TO INPUT)

FOR THE FILTER I/O

BOLD (NOT UNDERLINED): DECIMATED FILTER OUTPUT OR UNFILTERED INTERPOLATION TO OUTPUT

BOLD (UNDERLINED): UNFILTERED INTERPOLATION TO OUTPUT AND ALSO FIRST FILTER INPUT


UNDERLINED: FILTER INPUT NOT CORRESPONDING TO AN OUTPUT OR THE FILTER OUTPUT SITING

ITALIC: FILTER INPUT AND ALSO THE TIME CORRESPONDING TO THE FILTER OUTPUT SITING

-: UNUSED INTERPOLATION OUTPUT

TABLE 2

U/V VS Y PIXEL SITING, VERTICAL

4:2:2 > 4:2:2
2:1 DECIMATE4:2:2 > 4:2:0
2:1 DECIMATE4:2:2 > 4:2:0
4/3 UPSCALE

LEGEND:

- Y Y PIXEL INPUT/OUTPUT
- O U OR V PIXEL INPUT/OUTPUT
- I MAPPED INTERPOLATION POINT (OUTPUT TO INPUT)

FOR FILTER I/O:

- BOLD:** DECIMATED FILTER OUTPUT OR UNFILTERED INTERPOLATION TO OUTPUT
- UNDERLINED: FILTER INPUT NOT CORRESPONDING TO AN OUTPUT OR THE FILTER OUTPUT SITING
- ITALICS:* FILTER INPUT AND ALSO THE LINE CORRESPONDING TO THE FILTER OUTPUT SITING

TABLE 3

NTSC/PAL DECODER/SCALER
U/V VS Y SCALER OUTPUT FUNCTIONS
(4:2:2 INPUT VIDEO ASSUMED)

OPERATION	Σd_{UV}	POINT OUTPUT	STARTER U, V FILTER	U,V DECIMATE
4:2:2 > 4:2:2				
HORIZONTAL DOWNSCALE				
2:1	$1/2(\Sigma d_y) + 1/2(d_y)$ n even	n = 0	n = 2	2:1
4:1	$1/2 \Sigma d_y$, n even	n = 2	n = 6	4:1
8:1	$1/2 \Sigma d_y$, n even	n = 4	n = 12	8:1
VERTICAL				
UPSCALE	Σd_y	ALL	NONE	NONE
DOWNSCALE	Σd_y	NONE	n = 0	EQUALS Y
4:2:2 > 4:2:0				
HORIZONTAL DOWNSCALE	$1/2 \Sigma d_y$, n even	NONE	n = 0	EQUALS Y
VERTICAL				
UPSCALE	$(\Sigma d_y) + 1/2(d_y)$ n even	n = 0	n = 1	2:1
2:1	Σd_y	NONE	n = 0	4:1
4:1	Σd_y	NONE	n = 0	8:1
8:1	Σd_y	NONE	n = 0	16:1

Claims

1. A device for scaling an input of a first plurality of pixels arrayed in horizontal rows and vertical columns that form an image in order to provide an output of a second plurality of pixels that forms the image, the device comprising as a set an upscaling interpolator comprising (a) a buffer for storing the input pixels, and (b) a linear interpolator that sequentially receives each of the stored input pixels from said buffer and the pixel subsequent thereto for providing interpolated output pixels therefrom responsive to a predetermined upscaling factor, a decimating finite impulse response (FIR) filter for reducing the number of output pixels from said upscaling interpolator responsive to a predetermined downscaling factor, said second plurality being equal to said first plurality times said upscaling and

downscaling factors, and in which repetitive operation of said set of said upscaling interpolator and said decimating FIR filter will provide an output of the second plurality of pixels that forms the image.

2. A device as claimed in claim 1 wherein said set of said set of said upscaling interpolator and said decimating FIR filter is for horizontal scaling, and a second said set of said upscaling interpolator and said decimating FIR filter for vertical scaling, said two sets being arranged in series so that the output of one said set is the output of the other said set.
3. A device as claimed in claim 2 wherein said second set provides its output to the other said set.
4. A device as claimed in claim 2 wherein said set provides its output to said second set, and in which the predetermined upscaling and downscaling factors of said upscaling interpolator and said decimating FIR filter of said set are independent from the predetermined upscaling and downscaling factors of said upscaling interpolator and said decimating FIR filter of said second set.
5. A device as claimed in any one of claims 1 to 4 wherein said input pixels comprise luminance data and chrominance data, and said device comprises one said set of said upscaling interpolator and said decimating FIR filter for scaling said chrominance data, and a second said set of said upscaling interpolator and said decimating FIR filter for scaling said luminance data, and said input pixels comprise N color data components, and said device comprises N ones of said set of said upscaling interpolators and said decimating FIR filters, and said decimating FIR filter decimates in powers of two.
6. A device as claimed in any one of claims 1 to 5 wherein said upscaling factor is at least one and no greater than two, in which said buffer comprises two row buffers.
7. A device as claimed in any one of claims 1 to 6, including an interpolator for increasing the number of input pixels to a third plurality of interpolated pixels, a decimating-by-power-of-two FIR filter for reducing the number of interpolated pixels to said second plurality of output pixels, and each said interpolator is responsive to a scaling factor of at least one and no greater than two, said scaling factor for each said interpolator being independent of said scaling factor for the other said interpolator, in which one said interpolator comprises one row buffer and one said FIR filter comprises N taps, with N being one greater than the power of two decimation of said one FIR filter, or preferably one said interpolator comprises two row buffers and one said FIR filter comprises N taps, with N being three greater than the power of two decimation of said one FIR filter.
8. A device for scaling an input of a first plurality of pixels arrayed in horizontal rows and vertical columns that form an image in order to provide an output of a second plurality of pixels that forms the image, each of the pixels having N color components, the device comprising, first means for vertically scaling pixels, second means for horizontally scaling pixels connected in series with said first means, each of said first and second means comprising plural sets of an upscaling interpolator and a decimating FIR filter connected in series therewith, each of said sets for scaling at least one of said N color components, in which at least one of said sets is for scaling two of said N color components, and for subsampling said two color components at a rate related to a decimating power of said FIR filter.
9. A device as claimed in claim 8 wherein said N color components are Y, U, and V components, and for subsampling said U and V components at a rate related to a decimating power of said FIR filter, and another of said sets is for scaling said Y components without subsampling.
10. A method of scaling an input of a first plurality of pixels that form an image to provide an output of a second plurality of pixels that forms the image, the method comprising the steps of:
 - (a) upscaling the input pixels in an interpolator responsive to an upscaling factor; and
 - (b) decimating the upscaled pixels in decimation-by-power-of-two-FIR filter, the upscaling factor being selected so that the subsequent decimation by power of two provides the second plurality of pixels.
11. A method as claimed in claim 10 wherein steps (a) - (b) are for vertically scaling responsive to a vertical scaling factor, and further comprising the step of horizontally scaling the vertically scaled image responsive to a horizontal scaling factor by repeating steps (a) - (b).




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6